



## Incharge® Lumin 67W™

Charger

User manual

EN

### Product presentation:

Compact GaN wall charger with a TFT display that not only charges quickly but also shows all operating parameters in real-time – voltage, current, power, temperature, and operating time. Three ports (2×USB-C, 1×USB-A) with a total power of 67 W and intelligent power distribution allow you to charge a smartphone, tablet, and laptop simultaneously.

Full compatibility with PD 3.0, QC 4+, PPS, SCP, AFC, and FCP protocols ensures that it can effortlessly power an iPhone, Samsung, MacBook, Nintendo Switch, or ultrabook. Advanced protections and continuous temperature monitoring guarantee complete safety, and its compact, robust housing makes it suitable for use at home, in the office, or on the go.

### Package contains:

- Incharge® Lumin 67W™
- user manual

### Technical specifications:

**Model:** INCL67W1A2CTFT

**Dimensions:** 35.6 × 51.7 × 67.9 mm (without plug)

**Weight:** 164 g net

**Colour:** Black / Graphite

**Housing material:** Flame retardant material (PC/ABS)

**Technology:** GaN (gallium nitride)

**Ports:** 3 ports: 2×USB-C, 1×USB-A

**Total power:** 67 W (65 W during simultaneous operation)

**Input:** 100–240 V ~ 50/60 Hz, 1.6 A Max

**USB-C1 / USB-C2 Output:** 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3.35A (67 W Max), PPS: 3.3–11V/5A, 3.3–21V/3A (63 W Max)

**USB-A Output:** 5V/4.5A, 4.5V/5A, 9V/3A, 12V/2.5A, 20V/1.5A (30 W Max)

**Supported protocols (USB-C):** Apple 2.4A, Samsung 5V/2A, DCP 5V/1.5A, QC 2.0/3.0/4+, AFC, FCP, SCP, PD 3.0, PPS

**Supported protocols (USB-A):** Apple 2.4A, Samsung 5V/2A, DCP 5V/1.5A, QC 2.0/3.0, AFC, FCP, SCP

**Energy efficiency:** ≥ 85% at rated load; meets EU directive requirements for external power supplies

**Compatibility:** Smartphones (iPhone, Samsung, Huawei, Xiaomi, Oppo, Realme, and others), tablets (iPad, Android), laptops (MacBook, Windows ultrabooks), power banks, portable consoles (Steam Deck, Nintendo Switch – handheld mode), USB accessories (e.g., TWS headphones, Bluetooth speakers)

### User manual:

**1. Plug the charger into the mains socket:**

Ensure the socket is functional and not damaged.

**2. Select the appropriate port:**

If charging a laptop or a high-power device – use the USB-C port.

If charging a phone, headphones, speaker, or other accessories – you can use either USB-C or USB-A.

### 3. Connect the cable:

Only use functional and certified cables (preferably original 3mk cables)

### 4. Connect the device:

The charger will automatically recognize the connected equipment and adjust the power – you don't need to set anything.

### 5. Monitor the TFT screen (optional):

#### **On the screen, you can check:**

- how much power each device is consuming,
- total charging power,
- the operating temperature of the charger,
- the total operating time.

*The button to toggle information on the display is located on the top of the housing.*

### 6. Charge safely:

Do not cover the charger while in use to allow it to cool down.

If the screen shows a high temperature or if you feel the charger is very hot – disconnect it.

### 7. After charging is complete, disconnect the device:

Do not leave the charger plugged in unnecessarily for long periods.

### Safe usage instructions:

- Use only indoors, in dry conditions
- Do not use outdoors
- Do not expose the device to direct sunlight or rain
- Do not connect to overloaded power strips or sockets that have too many devices connected
- Do not cover the charger while in use
- Only use certified cables (PD/QC) and original 3mk cables
- Do not use damaged wires or devices
- Keep out of reach of children
- Do not open or disassemble the device – risk of electric shock
- In case of overheating or unusual smell, immediately unplug from the wall

### Warranty:

Improper use or incorrect placement of this product by users may result in a shortened lifespan or damage, and any resulting consequences are not covered by the warranty or the manufacturer's liability. The warranty covers manufacturing defects and material faults. The manufacturer's warranty is 24 months.

### Disposal and recycling information:

This symbol on the product, battery, documentation or packaging indicates that products and batteries should be handed over to designated waste collection points after their useful life has ended. This ensures that WEEE waste is recycled and processed in a way that protects valuable materials and human health and the environment.

### Declaration of conformity:

Hereby, 3mk Sp. z o.o. declares that this product complies with the appropriate EU harmonization legislation 2011/65/EU. The full text of the declaration of conformity is available at the following website ([3mk.global/manual](http://3mk.global/manual)).

### Designed in Poland by:

3mk Protection Sp. z o.o.  
Krotoszyńska 35, B-02/4a  
63-400 Ostrów Wielkopolski  
VAT ID PL 6222833086  
[3mk@3mk.pl](mailto:3mk@3mk.pl)

### Made in China.

