




Double Car Charger PD 135W™

Charger

User manual

EN



Product Appearance:

This car charger consists of two parts:

- main car charger
- rear seat charger

1. USB-C 3.0 PD 65W socket
2. USB-C PD 3.0 20W socket
3. USB-A QC 3.0 18W socket
4. 1.5m cable
5. USB-C PD 3.0 30W socket
6. LED indicator
7. USB-C PD 3.0 20W socket
8. USB-A QC 3.0 18W socket
9. rear clip

Product Presentation:

This product is a dual car charger with a power of 135W, allowing for charging up to 6 devices simultaneously in

the front and rear seats of the car. Both parts of the charger have three output ports for charging: 2 x USB-C and 1 x USB-A. The 65W USB-C port allows for charging laptops. The device is equipped with backlighting for easier location in the car.

Package Contents:

- 3mk Double Car Charger PD 135W™
- User manual

Technical Specification:

- Model Name: 3mk Double Car Charger PD 135W™
- Model Number: CC001
- Input Voltage: DC 12V/24V
- Output Voltage: below

Front seats (85W):

USB-C1: 5V-15V/3A, 20V/3.25A, PPS 3.3-11V/5A (PD 65W - using 5A cable)

USB-C2: 5V/3A, 9V/2.22A, 12V/1.67A (PD 20W)

USB-A1: 5V/3A, 9V/2A, 12V/1.5A (QC 18W)

USB-C2+USB-A1: 5V/3A (20W)

Rear seats (50W):

USB-C3: 5V/3A, 9V/3A, 12V/2.5A, PPS 3.3-11V/3A (PD 30W)

USB-C4: 5V/3A, 9V/2.22A, 12V/1.67A (PD 20W)

USB-A2: 5V/3A, 9V/2A, 12V/1.5A (QC 18W)

USB-C4+USB-A2: 5V/3A (20W)

- Output Current: 10A
- Output Power: 135W
- Cable Length: 1.5m
- LED Backlighting
- Energy Efficiency: 85%, for USB-C1 65W 93%
- Material: ABS + PC
- Compatible with most phones, tablets, laptops, and other devices powered via USB ports

User Instructions:

Unless the user manual of the devices you wish to charge clearly states otherwise, proceed as follows:

- Connect the car charger to the vehicle;
- Clip the charger to the pocket in the rear seat;
- Connect the device to the charger using the appropriate cable;
- Enjoy safe charging of any USB-compatible devices.

The main car charger is connected to the front cigarette lighter socket, powering both the main charger and the rear seat charger.

The main car charger features 3 USB ports with a maximum power of 85W, allowing for charging a tablet, mobile phone, laptop - up to 3 devices simultaneously. A 1.5m cable connects the main car charger to the rear seat charger. The rear seat charger is also equipped with 3 USB ports with a maximum power of 50W, allowing for

charging a tablet, mobile phone, and other USB-powered devices - also up to 3 devices simultaneously.

Warnings:

- Protect the product from dirt, moisture, and overheating and use it only in dry rooms.
- Do not drop the product and do not expose it to severe shocks.
- Do not use the product beyond the power limits indicated in the specifications.
- Do not modify the device in any way. Such actions void the warranty.
- Do not continue to use the device if it is visibly damaged.
- Use the product only for its intended purpose.
- Store this product, like all electrical products, out of reach of children!
- Do not use the product in direct proximity to radiators or other heat sources or in direct sunlight.
- Remove the packaging material immediately in accordance with local regulations.
- Use the item only in moderate climate conditions.
- Do not use the product in a humid environment and avoid splashes.
- Do not open the device or continue to use it if it becomes damaged.

- Do not attempt to service or repair the product yourself. All servicing should be performed by qualified personnel.
- Do not exceed the maximum load for the cigarette lighter sockets.

Warranty:

Improper use or incorrect placement of this product by users may result in a reduction of its lifespan or damage, and any resulting damages are not covered by warranty or are beyond the manufacturer's liability. The warranty covers factory defects and material faults. The manufacturer's warranty is 24 months.

Disposal and Recycling Information:

This symbol on the product, battery, documentation, or packaging indicates that products and batteries should be handed over to designated waste collection points after the end of their life cycle. This ensures that WEEE waste is recycled and processed in a manner that conserves valuable materials and protects human health and the environment.

Declaration of Conformity:

Hereby, 3mk Protection declares that the product complies with relevant community harmonisation

legislation. The full text of the declaration of conformity is available at the following website: 3mk.global/manual.

Designed in Poland by:

3mk Protection Sp. z o.o.
Krotoszyńska 35, B-02/4a
63-400 Ostrów Wielkopolski
VAT ID PL 6222833086
3mk@3mk.pl

Manufactured in China.

